

ANT-04

Frequency Range	30 MHz to 3 GHz
Primary Sensor	H-field
Correction Factor / Frequency Response	10 dB / -26.5 dB (Avg.)
Deviation of Correction Factor	± 4 dB
Connector	50 Ω (SMA)
Maximum Input Power	0.5 W

ANT-05

Frequency Range	30 MHz to 3 GHz
Primary Sensor	H-field
Correction Factor / Frequency Response	10 dB / -26.5 dB (Avg.)
Deviation of Correction Factor	± 4 dB
Connector	50 Ω (SMA)
Maximum Input Power	0.5 W

PR-01

Frequency Range	150 kHz to 30 MHz
Primary Sensor	E-field
Insertion Loss S21 / Frequency Response	5 dB / -3.6 dB (Avg.)
Deviation of Insertion Loss S21	± 1 dB
Connector	50 Ω (SMA)
Input Resistance	10 M Ω
Rated Voltage	300 VAC

PR-02

Frequency Range	30 MHz to 3 GHz
Primary Sensor	E-field
Insertion Loss S21 / Frequency Response	10 dB / -13.5 dB (Avg.)
Deviation of Insertion Loss S21	± 3 dB
Connector	50 Ω (SMA)
Input Resistance	1 M Ω
Maximum Permissible Voltage at Probe Tip	50 VDC